

TITLE OF THE INVENTION
IMAGE SENSING APPARATUS AND CONTROL METHOD THEREOF

FIELD OF THE INVENTION

5 The present invention relates to an image sensing apparatus, such as a digital camera, and a control method thereof.

BACKGROUND OF THE INVENTION

10 Conventionally, image sensing apparatus such as digital camera is known which records and reproduce a still picture or an moving picture with a recording medium such as a memory card having a solid state memory device as a recording medium. Some type of such an apparatus is
15 provided with not only an optical finder (OVF) but also an electronic finder composed of a color liquid crystal panel or the like.

 Such image sensing apparatus with an electronic finder often keeps sensed images displayed on the electronic
20 finder successively even when the sensed images are not actually recorded or stored on a storage medium. Under these circumstances, the operations for recording the sensed images, such as focusing and image saving, start only when the shutter is pressed.

25 With the above-mentioned conventional image sensing apparatus equipped with an electronic finder, however, keeping sensed images displayed on the electronic finder

during image sensing reduces the number of shots that can be taken because a large amount of power is consumed by the electronic finder, resulting in battery drain. On the other hand, lowering the operating frequency of the entire apparatus too much to reduce power consumption is not practical because it will increase the shutter time lag, the time required for the image sensing to be actually carried out after the shutter is pressed.

10 SUMMARY OF THE INVENTION

The present invention has been made to solve the problems of the prior art described above. An object of the present invention, for example, is to achieve power savings without increasing the shutter time lag.

15 According to the present invention, there is provided an image sensing apparatus, comprising:

an image sensor that senses an image of a subject to obtain a sensed image;

20 an operating frequency setting device that is capable of setting the operating frequency of said image sensing apparatus to at least any of a first operating frequency or a second operating frequency different from said first operating frequency; and

25 a display unit that is capable of electrically displaying the sensed image obtained by said image sensor, the display unit being capable of display operations at any

of said first or second operating frequency set by said operating frequency setting device.

According to the present invention, there is also provided a method for controlling an image sensing apparatus, comprising:

an image sensing step that senses an image of a subject to obtain a sensed image;

an operating frequency setting step that sets the operating frequency of said image sensing apparatus to at least any of a first operating frequency or a second operating frequency different from said first operating frequency at least; and

a display step that electrically displays the sensed image obtained in said image sensing step, in said display step said sensed image being displayed at said first or second operating frequency set in said operating frequency setting step.

According to the present invention, there is also provided a storage medium that stores a control program of an image sensing apparatus, said control program comprising:

a code for an image sensing step that senses an image of a subject to obtain a sensed image;

a code for an operating frequency setting step that sets the operating frequency of said image sensing apparatus to at least any of a first operating frequency

or a second operating frequency different from said first operating frequency; and

a code for a display step that electrically displays the sensed image obtained in said image sensing step, in
5 said display step said sensed image being displayed at said first or second operating frequency set in said operating frequency setting step.

Other features and advantages of the present invention will be apparent from the following description taken in
10 conjunction with the accompanying drawings, in which like reference characters designate the same or similar parts throughout the figures thereof.

BRIEF DESCRIPTION OF THE DRAWINGS

15 The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate embodiments of the invention and, together with the description, serve to explain the principles of the invention.

20 FIG. 1 is a block diagram showing the configuration of the image sensing apparatus according to a first embodiment of the present invention; and

FIGS. 2 to 5 are flowcharts of image sensing processing.

25

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of the present invention will now be described in detail in accordance with the accompanying drawings.

FIG. 1 is a block diagram showing the configuration of the image sensing apparatus according to a first embodiment of the present invention. This device is configured, for example, as a digital camera.

In the figure, reference numeral 100 denotes an image processing apparatus (image sensing apparatus), 10 denotes a taking lens consisting of a zoom lens and focusing lens, 12 denotes a shutter provided with an aperture adjustment function, and 14 denotes an image sensing device, which converts an optical image into an electrical signal. Reference numeral 16 denotes an A/D converter, which converts the analog signal output of the image sensing device 14 into a digital signal. Reference numeral 18 denotes a timing generator circuit, which supplies clock signals and control signals to the image sensing device 14 and A/D converter 16 and is controlled by a memory control circuit 22 and system control circuit 50.

Reference numeral 20 denotes an image processing circuit, which performs designated pixel interpolation or color conversion on the data from the A/D converter 16 or data from the memory control circuit 22. The image processing circuit 20 carries out designated computations using sensed image data. Based on the computed results, the system control circuit 50 instructs the exposure

controller 40 and focusing controller 42 to perform TTL (through-the-lens) mode AF (autofocusing), AE (automatic exposure), and EF (preflashing) processes. Moreover, the image processing circuit 20 carries out designated
5 computations using sensed image data, and based on the computed results, it performs a TTL mode AWB (automatic white balance) adjustment.

Reference numeral 22 denotes the memory control circuit, which controls the A/D converter 16, the timing
10 generator circuit 18, the image processing circuit 20, an image display memory 24, a D/A converter 26, a memory 30, and a compression/decompression circuit 32.

The data from the A/D converter 16 is written into the image display memory 24 or memory 30 via the image
15 processing circuit 20 and memory control circuit 22 or directly via the memory control circuit 22.

Reference numeral 24 denotes the image display memory, 26 denotes the D/A converter, and 28 denotes an image display section constituted by a TFT-LCD (thin film
20 transistor liquid crystal display) and the like. The image data written into the image display memory 24 is displayed by the image display section 28 via the D/A converter 26. The image display section 28 can achieve the function of an electronic finder if it displays sensed image data
25 successively. Also, it can turn on and off the display at any time in accordance with instructions from the system control circuit 50. Turning off the display helps reduce

the power consumption of the image processing apparatus 100 greatly.

Reference numeral 30 denotes a memory for storing still pictures or moving pictures as well as voice data. It has
5 enough storage capacity to store a designated number of still pictures or designated minutes of moving pictures. This allows a large volume of image data to be written into the memory 30 at high speed even during sequential
photography or panoramic photography which involves taking
10 a series of still pictures successively. The memory 30 can also be used as a working area by the system control circuit 50.

Reference numeral 32 denotes a
compression/decompression circuit, which compresses and
15 decompresses image data through adaptive discrete cosine transform (ADCT) or the like. The circuit compresses or decompresses image data read from the memory 30 and writes the resulting data back into the memory 30.

Reference numeral 40 denotes an exposure controller,
20 which controls the shutter 12 and can have a flash control function if linked with a flash 404. Reference numeral 42 denotes a focusing controller, which controls the focusing of the taking lens 10. The exposure controller 40 and focusing controller 42 are controlled by means of a TTL
25 system. The system control circuit 50 controls the exposure controller 40 and focusing controller 42, based

on the results of the computations performed by the image processing circuit 20 on sensed image data.

Reference numeral 44 denotes a zoom controller, which controls the zooming of the taking lens 10. Reference numeral 46 denotes a barrier controller, which controls a protector 102 that serves as a barrier. Reference numeral 48 denotes a connector, also known as an accessory shoe, which incorporates an electric contact and mechanical clamp for flash apparatus 400.

Reference numeral 50 denotes a system control circuit, which controls the entire image processing apparatus 100. Reference numeral 52 denotes a memory, which stores the constants, variables, programs, etc. for the operation of the system control circuit 50.

Reference numeral 54 denotes a display section, which is constituted by a liquid crystal display, speaker, etc. This section displays operating state, messages, and the like using characters, images, voice, etc. according to the program executed by the system control circuit 50. The display section 54 is installed at one or more readily visible locations near input devices of the image processing apparatus 100 and constituted by, for example, a combination of an LCD (liquid crystal display), LEDs (light emitting diodes), sound-producing elements and the like.

Reference numeral 56 denotes an electrically erasable programmable non-volatile memory such as an EEPROM.

(electrically erasable and programmable read only memory).
Reference numerals 60, 61, 62, 64, 66, and 70 denote input
devices, via which various instructions for the system
control circuit 50 are entered and which are constituted
5 by one or more switches, dials, touch panels, pointing
devices employing line-of-sight detection, speech
recognition devices, etc. or their combinations.

Now the input devices 60, 61, 62, 64, 66, and 70 will
be described concretely.

10 Reference numeral 60 denotes a power switch that turns
on and off the image processing apparatus 100. Reference
numeral 61 denotes a mode dial switch, which allows
selection among various modes such as automatic shooting
mode, manual shooting mode, panoramic photography mode,
15 playback mode.

Reference numeral 62 denotes a shutter switch (SW1),
which turns on halfway through the release operation of a
shutter button (not shown) and gives the command to start
AF (autofocusing), AE (automatic exposure), AWB (automatic
20 white balance), EF (preflashing), and other processes.

Reference numeral 64 denotes a shutter switch (SW2),
which turns on when the release operation of the shutter
button (not shown) is completed and triggers a sequence of
processes: an exposure process of writing the signals read
25 out of the image sensing device 12 into the memory 30 as
image data through the A/D converter 16 and memory control
circuit 22; developing process using the computations

carried out in the image processing circuit 20 and memory control circuit 22; and recording process of reading image data out of the memory 30, compressing it in the compression/decompression circuit 32, and writing it in a recording medium 200 or recording medium 210.

Reference numeral 66 denotes an image display ON/OFF switch, which allows the image display section 28 to be set to ON or OFF. This function makes it possible to shut off the current to the image display section constituted by an TFT-LCD, etc. during photography by the use of an optical finder 104, and thereby save power. The ON/OFF setting of the image display section 28 is stored as an image display flag (ON/OFF) in a memory 52. The user can set the image display flag at will using the input device 70. The setting may also be stored in an internal memory of the system control circuit 50.

A zoom switch (not shown) instructs zooming of the taking lens 10.

Reference numeral 70 denotes the input device, which consists of various buttons, a touch panel, etc., including a menu button, set button, macro button, multi-screen playback/page-break button, flash setting button, single-shot/multi-shot self-timer switchover button, menu forward (+) button, menu backward (-) button, image forward (+) button, image backward (-) button, menu up button, menu down button, picture quality selection button, exposure compensation button, date/time setting button, etc.

Reference numeral 80 denotes a power supply controller, which is constituted by a battery detector circuit, DC/DC converter, and switching circuit for switching the block to turn on. This controller detects the presence or absence of a battery, type of battery, and remaining battery capacity, and supplies required voltages for required periods of time to various parts of the system, including the recording media 200 and 210, by controlling the DC/DC converter, based on the results of the detection and instructions from the system control circuit 50.

Reference numerals 82 and 84 denote connectors while reference numeral 86 denotes a power supply, which is constituted by a primary battery such as an alkaline or lithium cell, secondary battery such as an NiCd, NiMH, or Li cell, AC adaptor, etc.

Reference numerals 90 and 94 denote interfaces (I/F) to the recording media 200 and 210 such as memory cards or hard disks while reference numerals 92 and 96 denote connectors for connecting to the recording media 200 and 210 such as memory cards or hard disks.

Reference numeral 98 denotes a media detector, which detects whether the recording medium 200 or 210 has been inserted in the connectors 92 and/or 96.

This embodiment has two sets of an interface and connector for connecting storage media. Of course, the present invention may be configured to have either one set or multiple sets of an interface and connector for

connecting recording media. Also, it may be configured to have a combination of interfaces and connectors of different standards.

Cards that comply with PCMCIA, CF (compact flash), or other similar standards may be used as the interfaces and connectors. When cards that comply with PCMCIA, CF (compact flash), or other similar standards are used for the interfaces 90 and 94 and connectors 92 and 96, if communications cards such as a LAN card, modem card, USB card, IEEE1394 card, P1284 card, SCSI card, and/or telecommunication card for PHS are connected, image data and accompanying management information can be exchanged with other computers or peripherals such as printers.

Reference numeral 102 denotes the barrier or protector 102, which covers an image sensing section including the taking lens 10 of the image processing apparatus 100 to protect the image sensing section from contamination and damage. Reference numeral 104 denotes the optical finder, which allows the user to take photographs only by using the optical finder 104 without using the electronic finder function of the image display section 28. Besides, the optical finder 104 incorporates some of the functions of the display section 54: for example, an in-focus indicator function, blur warning function, flash charge indicator function, shutter speed indicator function, f-number indicator function, exposure compensation indicator function.

Reference numeral 110 denotes a communications section, which has various communications functions such as RS232C, USB, IEEE1394, P1284, SCSI, modem, LAN, and wireless communications functions. Reference numeral 112
5 denotes either a connector used to connect the image processing apparatus 100 to other equipment through the communications section 110 or an antenna used for wireless communications.

Reference numeral 200 denotes the storage medium such
10 as a memory card or hard disk. The storage medium 200 has a recording section 202 constituted by a semiconductor memory, magnetic disk, or the like; an interface (I/F) 204 to the image processing apparatus 100; and a connector 206 for connecting to the image processing apparatus 100.

Reference numeral 210 denotes the storage medium such
15 as a memory card or hard disk. The storage medium 210 has a recording section 212 constituted by a semiconductor memory, magnetic disk, or the like; an interface (I/F) 214 to the image processing apparatus 100; and a connector 216
20 for connecting to the image processing apparatus 100.

Reference numeral 400 denotes the flash apparatus and
402 denotes a connector for connecting to the accessory shoe of the image processing apparatus 100. Reference numeral 404 denotes a flash, which is provided with an AF fill-
25 flash function and flash control function.

With the above configuration, if the mode dial switch 61 is set at image sensing mode, the image sensing can be

carried out with the shutter switch (SW1) 62 and shutter switch (SW2) 64. The system control circuit 50 is normally ready for photography. If a press of the shutter switch (SW1) 62 is detected, the exposure controller 40 controls exposure and the focusing controller 42 controls focusing. When these control operations are completed, the system gets ready to start exposure. When a press of the shutter switch (SW2) 64 is detected, the exposure is started. The sensed image acquired by photography is stored in the memory 30 via the image sensing device 14, A/D converter 16, image processing circuit 20, and memory control circuit 22. The recorded image stored in the memory 30 are compressed by the compression/decompression circuit 32 as required, and stored again in the memory 30. The system control circuit 50 finishes photography in this state.

FIGS. 2 to 5 are drawings showing flowcharts of the image sensing processing according to this embodiment.

First, during initialization, i.e., upon power-up after a battery replacement or the like, the system control circuit 50 initializes flags and control variables (Step S101). Next, the system control circuit 50 checks the state of the power switch 60 to see if it is set at ON (Step S102). If the power switch 60 is set at OFF, the system control circuit 50 performs finishing processes (Step S105). Specifically, it finishes the display in the display sections, closes the barrier of the protector 102 to protect the image sensing section, stores necessary set values and

mode settings as well as the settings of necessary parameters including flags and control variables in the non-volatile memory 56, shuts off unnecessary power to individual sections of the image processing apparatus 100 including the image display section 28 by means of the power supply controller 80, and performs other designated finishing processes. Then the flow returns to the Step S102.

On the other hand, if it is found in the Step S102 that the power switch 60 is set at ON, the system control circuit 50 checks the setting position (either photo mode or playback mode) of the mode dial switch 61 to see if it is set at photo mode (Step S103). If it is found that the mode dial switch 61 is set at playback mode, the system control circuit 50 runs the playback process (Step S104) and returns to the Step S102.

If the mode dial switch 61 is set at photo mode, the system control circuit 50 checks the remaining capacity and operating state of the power supply 86 by using the power supply controller 80 to see if the operation of the image processing apparatus 100 will not be hampered (Step S106). If it is judged that the operation of the image processing apparatus 100 will be hampered, the system control circuit 50 goes to Step S109. If it is judged that the operation of the image processing apparatus 100 will not be hampered, the system control circuit 50 checks the operating state of the recording medium 200 or 210 to see if the operation

of the image processing apparatus 100, especially the recording and playback operations of image data with respect to the recording medium 200 or 210, will not be hampered (Step S107). If it is judged that the operation
5 of the image processing apparatus 100 will be hampered, the system control circuit 50 goes to Step S109. If it is judged that the operation of the image processing apparatus 100 will not be hampered, the system control circuit 50 initializes the taking lens 10 and checks if it operates
10 normally (Step S108). If it is judged that the taking lens 10 does not operate normally, the system control circuit 50 goes to Step S109.

In Step S109, the system control circuit 50 displays warnings in the display section 54, etc. using images or
15 voice. Then the flow returns to the Step S102.

On the other hand, if it is judged in the Step S108 that the taking lens 10 operates normally, the system control circuit 50 checks if the image display flag is ON (Step S110 in FIG. 3). If it is found that the image display
20 flag is ON, the system control circuit 50 switches the operating frequency W of the present apparatus as a whole to a first operating frequency W1 (Step S118).

The operating frequency W of the present apparatus is set either at the first operating frequency W1 or at a second
25 operating frequency W2 higher than it. At the start of processing (initialization) in FIG. 2, it is set at the second operating frequency W2. Therefore, in the Step S118,

the operating frequency W is switched from the second operating frequency W2 to the first operating frequency W1, the lower frequency. This reduces power consumption. The switching of the operating frequency W is controlled by the
5 system control circuit 50.

Next, the system control circuit 50 checks the state of image display in the image display section 28 to see if the image display in the image display section 28 is ON (Step S119). If it is found that the image display in the image display section 28 is not ON, the system control circuit
10 50 turns on the image display in the image display section 28 (Step S120), puts it in through-display mode so that sensed image data will be displayed successively (Step S121), and goes to Step S122. On the other hand, if it is
15 found that the image display in the image display section 28 is ON, the system control circuit 50 goes to the Step S122 immediately. In the through-display mode described above, the data written successively into the image display memory 24 via the image sensing device 14, A/D converter
20 16, image processing circuit 20, and memory control circuit 22 is displayed successively in the image display section 28 via the memory control circuit 22 and the D/A converter 26 to implement the function of an electronic finder.

In the following Step S122, the system control circuit
25 50 checks to see if a setting state indicator flag is ON. If it is ON, the system control circuit 50 displays the setting state in the image display section 28 (Step S123)

and goes to Step S131 in FIG. 4. On the other hand, if the setting state indicator flag is not ON, the system control circuit 50 goes to the Step S131 immediately.

If it is found in the Step S110 that the image display flag is not ON (i.e., the flag is OFF), the system control circuit 50 checks to see if the setting state indicator flag is ON (Step S111). If the setting state indicator flag is not ON, the system control circuit 50 goes to the Step S131 immediately. If the setting state indicator flag is ON, the system control circuit 50 turns on the image display in the image display section 28 (Step S112), displays the setting state in the image display section 28 (Step S113), and checks to see if a preset setting state display time has expired (Step S114). The system control circuit 50 continues the checking until the setting state display time expires. When the setting state display time expires, the system control circuit 50 turns off the setting state indicator flag (Step S115), clears the setting state display in the image display section 28 (Step S116), turns off the image display in the image display section 28 (Step S117), and goes to the Step S131.

In the following Step S131 in FIG. 4, the system control circuit 50 checks to see if the shutter switch (SW1) 62 is ON. If it is found that SW1 is not ON, the system control circuit 50 checks to see if the image display flag is ON (Step S152). If it is found that the image display flag is ON, the system control circuit 50 performs metering (Step

S153) and AWB adjustment (Step S154) and returns to the Step S102 in FIG. 2. On the other hand, if it is found that the image display flag is not ON, the system control circuit 50 returns to the Step S102 immediately.

5 If it is found in the Step S131 that the shutter switch (SW1) 62 is ON, the system control circuit 50 checks to see if the image display flag is ON (Step S132). If it is found that the image display flag is ON, the system control circuit 50 goes to Step S134. If it is found that the image display flag is not ON, the system control circuit 50 switches the operating frequency W (Step S133) before going to the Step S134.

10 This process of switching the operating frequency W changes the operating frequency W of the present apparatus as a whole from the first operating frequency W1 to the second operating frequency W2. Thus, the operating frequency W returns to its normal rate. This ensures that subsequent recording operations of sensed images, including metering, focusing control, and recording/saving operations, will be carried out at high speed.

15 Next, in Step S134, metering is performed. During metering, flash settings are made as required. In the following Step S135, focusing control is performed to focus the taking lens on the subject.

25 In the following Step S138, the system control circuit 50 checks to see if the shutter switch (SW2) 64 is ON. If it is found that SW2 is not ON, the system control circuit

50 checks to see if the shutter switch (SW1) 62 is ON (Step S139). If it is found that SW1 is not ON (has been turned off), the system control circuit 50 returns to the Step S102. If it is found that SW1 is ON (remains ON), the system control circuit 50 returns to the Step S138. If it is found in the Step S138 that the shutter switch (SW2) 64 is ON, the system control circuit 50 checks to see if the image display flag is ON (Step S140 in FIG. 5).

If it is found that the image display flag is ON, the system control circuit 50 sets the display mode in the image display section 28 to fixed color display mode (Step S141) and goes to Step S142. If it is found that the image display flag is not ON, the system control circuit 50 goes to the Step S142 immediately. In the fixed color display mode, instead of the sensed image data written into the image display memory 24 via the image sensing device 14, A/D converter 16, image processing circuit 20, and memory control circuit 22; fixed-color image data is received by the image display section 28 via the memory control circuit 22 and D/A converter 26 to display a fixed-color picture.

In the following Step S142, photographic processing is carried out. Specifically, the system control circuit 50 carries out exposure processing which involves writing photographic image data into the memory 30 via the image sensing device 14, A/D converter 16, image processing circuit 20, and memory control circuit 22 or directly from the A/D converter 16 via the memory control circuit 22 and

performs developing which involves reading the image data from the memory 30 using the memory control circuit 22 and, as required, image processing circuit 20 to perform various processing.

5 Next, the system control circuit 50 checks to see if the image display flag is ON (Step S143). If it is found that the image display flag is not ON, the system control circuit 50 turns on the image display in the image display section 28 (Step S144) and goes to Step S145. If it is found
10 that the image display flag is ON, the system control circuit 50 goes to Step S145 immediately.

 In Step S145, the system control circuit 50 displays a quick review. If the Step S144 is skipped, the image display section 28 continues to display the sensed image, serving the function of an electronic finder, and the quick
15 review is also displayed immediately after shooting. On the other hand, if the Step S144 is performed, the sensed image is not displayed for a quick review until just after shooting.

20 Next, the recording process of the sensed image data is carried out (Step S146). Specifically, this process involves reading the sensed image data from the memory 30, performing various image processing on it using the memory control circuit 22 and, as required, image processing
25 circuit 20, compressing it by the compression/decompression circuit 32 according to the mode

setting, and then writing it into the recording medium 200 or 210.

Next, the system control circuit 50 checks to see if the image display flag is ON (Step S147). If it is found
5 that the image display flag is ON, the system control circuit 50 sets the display mode to through-display (Step S148) and goes to Step S149. In the through-display mode, the sensed image data for the next shot is displayed successively after a quick review of the sensed image.

10 On the other hand, if it is found in the Step S147 that the image display flag is not ON, the system control circuit 50 turns off the image display in the image display section 28 (Step S150), turns on the setting state indicator flag (Step S151), and goes to the Step S149.

15 In the following Step S149, the system control circuit 50 checks to see if the shutter switch (SW1) 62 is ON. If it is found that SW1 is ON, the system control circuit 50 returns to the Step S138 to get ready for shooting. If it is found that SW1 is not ON (has been turned off), this means
20 that the sequence of photographic operations is finished and the system control circuit 50 returns to the Step S102.

According to this processing, if the image display flag is ON, the operating frequency W of the apparatus is set at the lower, first operating frequency W1 until the shutter
25 switch (SW1) 62 is pressed, and when the SW1 is pressed, the operating frequency W of the apparatus is switched to the second operating frequency W2, the normal frequency,

before metering, focusing control, etc. On the other hand, if the image display flag is OFF, the operating frequency W of the apparatus is constantly set at the normal, second operating frequency W2.

5 According to this embodiment, when a sensed image is displayed for image sensing, the apparatus operates at the lower, first operating frequency W1 until the shutter switch (SW1) 62 is pressed triggering the operations (metering, focusing control, saving, etc.) for recording
10 the sensed image. This effectively reduces power consumption, which tends to be increased by the image display in the image display section 28. Besides, during the recording of sensed images, the apparatus operates at the normal, second operating frequency W2 to increase the
15 processing speed and reduce the shutter time lag. Thus, power savings can be achieved without increasing the shutter time lag.

When the image sensing is carried out without sensed image display, since the image display section 28 consumes
20 less power from the beginning, the decrease in the operating frequency is less effective in power savings. Therefore, the apparatus is always made to operate at the normal, second operating frequency W2 to give priority to the processing speed and avoid increasing the shutter time lag
25 more reliably.

Although in this embodiment, the process of lowering the operating frequency W to the first operating frequency

W1 is applied to the entire apparatus, it is also possible to apply this process only to the operations (image sensing operation by the image sensing device 14, display operation by the image display section 28, etc.) directly relevant to the image display in the image display section 28.

Although in this embodiment, the timing of switching the operating frequency W from the first operating frequency W1 back to the second operating frequency W2 is provided after SW1 is pressed but before the metering (Step S134) to reduce the shutter time lag effectively, this timing is not limited to this time interval. It may be provided before the metering (Step S134), or after the shutter switch (SW2) 64 is pressed (Step S138) but before the photographic processing (Step S142).

As described above, when carrying out the image sensing while displaying an image, this embodiment can achieve power savings without increasing the shutter time lag, by using the low operating frequency before the recording operation is started or except during the recording operation.

When the sensed image is not displayed and thus less power saving effect is available, this embodiment can give priority to the processing speed and avoid increasing the shutter time lag more reliably.

Needless to say, the object of the present invention can also be achieved by a storage medium containing the software program code that implements the functions of the

above embodiments: it is supplied to an image sensing apparatus (image sensing apparatus 100), whose computer (or a CPU or MPU) (system control circuit 50) then reads the program code out of the storage medium and executes it.

5 In that case, the program code itself read out from the storage medium will implement the new functions of the above embodiments, and the storage medium which stores the program code will constitute the present invention.

10 As the storage medium for supplying the program code, for example, a floppy disk, hard disk, optical disk, magneto-optical disk, CD-ROM, CD-R, magnetic tape, non-volatile memory card, ROM, or the like may be used.

15 The functions of the above embodiments may be implemented not only by the program code read out and executed by the computer, but also by part or all of the actual processing executed, in accordance with instructions from the program code, by an OS (operating system) running on the computer.

20 Furthermore, the functions of the above embodiments may also be implemented by part or all of the actual processing executed by a CPU or the like contained in a function expansion card inserted in the computer or a function expansion unit connected to the computer if the processing is performed in accordance with instructions
25 from the program code that has been read out of the storage medium and written into memory on the function expansion card or unit.

As many apparently widely different embodiments of the present invention can be made without departing from the spirit and scope thereof, it is to be understood that the invention is not limited to the specific embodiments
5 thereof except as defined in the claims.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231